GF-P900E1-0999 Generator





Generator Configuration

Voltage	415
Control Panel	Comap MRS-16
Base Tank Type	Dual Wall
Circuit Breaker	4 Pole-Mot
Mains Charger	No
Lifting Frame	No
Forklift Pocket Skid	No
Water Jacket Heater	No

Alternator Data

Alternator Brand	LeRoy Somer
Alternator Model	LL7224L
Prime Amps per φ	1114
AVR Model	R450M
Volt Reg	+/- 0.5%
Insulation Class	Н
Winding Pitch	2/3
Excitation	AREP
Frequency (Hz)	50





Output Prime kVA	800
Output Prime kW	640
Enclosure Type	CAE
Fuel Capacity (L)	1494
Fuel Cons L/hr 100% Prime	171.2
Run HRs 100% Prime	8.7
Fuel Cons. @ 75% Load (L/Hr)	129.7
Fuel Cons. 50% Load (L/Hr)	92.0
Bunded	No

Engine Data

Perkins
Perkins
4006-23TAG3
6 - In Line
Electronic
Turbo Air to Air Charged
13.6:0
22.90
55
Replaceable Element
A2 Diesel
Replaceable Element
Spin-On, Full Flow
123.00
API CG4 15W-40

Prime Rating

These ratings are applicable for supplying continuous electrical power (at variable load) in lieu of commercially purchased power. There is no limitation to the annual hours of operation and this model can supply 10% overload power for 1 hour in 12 hours.

Standard Reference Conditions

Note: Standard reference conditions 25°C Air Inlet Temp, 100m MASL, 30% Relative Humidity, dB(A) are free field.

Mains Failure Transfer Panel (Option)	ATI1600
Noise (dBA) @ 1m 100% Load	89
Noise (dBA) @ 1m 75% Load	88
Noise (dBA) @ 7m 100% Load	81
Noise (dBA) @ 7m 75% Load	80



